



BT-STR5-SC Stopwatch controller

- + Hard-wired remote control unit for use of a digital clock of series BT-STx5-S as stopwatch (count-up and countdown)
- + Local time or countdown- resp. stopwatch-operation can be displayed
- + Single line display of hours, minutes and seconds on the clock
- + in stopwatch mode display of hours-minutes-seconds from 00:00:00 to 23:59:59 or countdown
- + Functions: Start, stop, split time, pre-selection, reset
- + with relay output, which is activated at the end of the count (up or down)
- + for example, by use of this relay an indicator light or a buzzer can be activated
- + Control buttons:
 - + A chronometer/clock display mode selector switch
 - + A counting up/down mode selector switch
 - + Two keys (H and M) for hour/minute pre-selection in counting down mode
 - + A reset key
 - + A split key for intermediate time display during 5 seconds
 - + A start/stop key
- + The timer control unit can control up to 10 digital clocks
- + Power supplied by the clock

Technical specifications:

Cable connection:	2-pair cable 4 x 0.5 mm ² (max. 20 m)
Signal relay:	8 A / 250 V
Protection class:	IP54
Current consumption:	20 mA
Operating temperature:	0 °C bis +50 °C
Dimensions (WxHxD):	90 x 147 x 45 mm (overall size)
Weight:	180 g

Option:

- + White embedded plate

